


LD0106-K12



Product Code:

LD0106-K12

| Electrical Data | |
|--|---|
| Mains Input Voltage (V) | 220-240 |
| Input Voltage Range (V) | 180-260 |
| Output Voltage (V) | AC 12V |
| Output Current (mA) | 500 |
| Power Factor (λ) | > 0.4 |
| Product Data | |
| Max. System Wattage (W) | 8 |
| Lamp Wattage (W) | 6 |
| Lamps Supported | All MEGAMAN® G4, MR11 and MR16 lamps with input voltage of AC 12V and maximum wattage of 6W |
| Dimmable | No |
| Ambient Temperature Range (Ta) | -10°C to +40°C |
| Maximum Casing Temperature (Tc) | 85°C |
| Weight (g) | 63 |
| Performance Data | |
| Rated Life (hrs) | 50000 |
| Luminaires of Protection Class | Class II |
| Product Dimensions | |
| Length (mm) | 100 |
| Width (mm) | 45 |
| Height (mm) | 25 |
| Push-in Terminals (mm ²) | 0.75-1.5 |
| Wire Preparation (mm) | 8 |
| Fixing Bracket for Screws | M4 |
| Remarks: The product is intended to be used as a lamp control gear. With open circuit, short circuit and over loaded protections | |

Product Code: LD0106-K12

MEGAMAN® 2005-2020. All Rights Reserved.

This document is for informational purpose only.

MEGAMAN® reserves the right to make changes from time to time in the interest of product developments without prior notification to any products herein.

www.cn.megaman.cc